

# Aastra 6750 digital terminals

Combining design with reliability

Aastra 6753

Aastra 6755

Aastra 6757



Aastra capitalises on the success of its SIP phones design to extend its range of digital terminals.

Aastra 6750 series comprises 3 terminals with the same user-friendly ergonomics.

An extension module (M670) including 36 programmable keys with LED is available on the Aastra 6757 terminal.

## Strong points of Aastra 6750

- **Aastra 6753, simplicity and elegance**

Aastra 6753 has a screen for quick display of caller and called-party name. Moreover, the call by name function gives access to the IPBX directory. It comprises 6 programmable keys and 2 other keys for multi-line management, for instance. An LED indicates to the user that a message has been left via voice mail, or that a call was missed.

- **Aastra 6755, for heavy callers**

Aastra 6755 has a large screen and 12 programmable keys, 6 of which have labels on the LCD screen. Its navigation key makes it easy to use. It is the ideal terminal for contact centres, because of its hands-free function and headset socket.

- **Aastra 6757, for the most demanding users**

Aastra 6757 also has a large screen for displaying the labels of 20 programmable keys and 5 interactive keys.

- Key labels on the LCD screen
- Sleek design
- Navigation key for terminals 6755 and 6757
- Homogeneity with the Aastra 6750i SIP range
- Compatibility with the installed base (as of release 3.2)



Aastra 6753



Aastra 6755



Aastra 6757

|   | 6753  | 6755                 | 6757                   |
|---|-------|----------------------|------------------------|
| <b>Features</b>   |       |                      |                        |
| Wall-mounting position  | •     | •                    | •                      |
| Headset socket  |       | •                    | •                      |
| <b>Screen</b>   |       |                      |                        |
| Screen (number of lines)  | 3     | 8<br>144 x 75 pixels | 11<br>144 x 128 pixels |
| Contrast management   | •     | •                    | •                      |
| <b>Keys</b>   |       |                      |                        |
| Direct access to voice mail   | •     | •                    | •                      |
| Redial  | •     | •                    | •                      |
| On-hook   | •     | •                    | •                      |
| R (Flash key)   | •     | •                    | •                      |
| Directory   | •     | •                    | •                      |
| Mute (LED)  | •     | •                    | •                      |
| Hands-free  |       | •                    | •                      |
| Loudspeaker (LED)   | •     | •                    | •                      |
| Intercom  |       | •                    | •                      |
| Number of programmable memory keys (LED)  | 6     | 12                   | 20 <sup>(1)</sup>      |
| Number of interactive keys  |       |                      | 5                      |
| Navigator   |       | •                    | •                      |
| Message indicator (call not consulted in log, incoming call signalling, voice mail) | •     | •                    | •                      |
| Transfer  | •(2)  | •(2)                 | •                      |
| Conference call   | •(2)  | •(2)                 | •                      |
| On-Hold   | •(2)  | •(2)                 | •                      |
| Do Not Disturb key  | •(2)  | •(2)                 | •                      |
| <b>Features</b>   |       |                      |                        |
| Call pick-up without lifting the handset  | •     | •                    | •                      |
| Speaker volume adjustment   | •     | •                    | •                      |
| Handset volume adjustment   | •     | •                    | •                      |
| Ringer adjustment: volume, tone   | •     | •                    | •                      |
| Ringer off  | •     | •                    | •                      |
| Number of ring tones  | 8     | 16                   | 16                     |
| Call by name  | •     | •                    | •                      |
| Multi-line  | •     | •                    | •                      |
| Size of private directory (numbers/lists)   |       | 20                   | 100                    |
| Size of terminal logs (incoming/outgoing calls=redial)                              | 1 / 5 | 10 / 50              | 10 / 50                |
| Date/time display   | •     | •                    | •                      |
| Name/number display   | •     | •                    | •                      |
| <b>Settings</b>   |       |                      |                        |
| M670 extension module (number/size)   |       |                      | 1 x 36 keys            |

(1) 5 keys available per page – a total of 4 pages

(2) Feature code

**Aastra France**  
 1 rue Arnold Schoenberg  
 78286 Guyancourt Cedex - France  
 Tél : 33 (0)1 30 96 42 00  
 Fax : 33 (0)1 30 96 43 00  
[www.aastra.fr](http://www.aastra.fr)

**Aastra Telecom United Kingdom**  
 Unit B3 Armstrong Mall - Southwood Business Park  
 Farnborough, Hampshire - GU14 0NR - United Kingdom  
 Tel: +44 (0) 1252 532100  
 Fax: +44(0) 1252 532101  
[www.aastra.co.uk](http://www.aastra.co.uk)

**Aastra**